



COMPACT HIGH-END STEREO NETWORK/CD/DAB/FM RECEIVER
WITH A MAX. POWER OUTPUT OF 150 WATTS IN HI-RES QUALITY



COMPACT HIGH-END STEREO
NETWORK/CD/DAB/FM
RECEIVER WITH A MAX. POWER
OUTPUT OF 150 WATTS IN
HI-RES QUALITY

- Amplifier and digital-to-analogue converter in certified Hi-Res quality
- MAGNAT STREAMING APP controls music streaming (Spotify™), internet radio and multiroom functions
- High-quality CD drive with precision laser unit and DAB+/FM tuner with large station memory
- Bluetooth® streaming (4.1) with the high-end audio standard Qualcomm® aptX™
- Digital inputs (e.g. for direct connection of a TV) plus additional analog inputs and subwoofer output
- Sturdy full-metal enclosure with solid aluminium front plate and controls



CD PLAYER:

- Repeat function (title/CD)
- Random function
- Title programming (up to 99 titles)
- CD audio, MP3 and WMA playback
- Supports CD text and ID3 tag

NETWORK FUNCTIONS:

- Internet radio
- Spotify™ audio streaming
- DLNA audio streaming
- Multiroom functions
- Own MAGNAT STREAMING APP for comfortable control of network functions

POWER AMPLIFIER AND POWER SUPPLY:

- Two analogue high-level inputs
- Additional 3.5 mm audio input on the front panel for connecting portable devices
- Digital inputs (1 x optical and 1 x coaxial) for sampling frequencies up to 192 kHz/24 bits, Hi-Res certified
- Bluetooth® input (4.1) supports the high-end audio standard Qualcomm® aptX™
- Analogue output for connecting a powered subwoofer
- Record Out fixed level output
- Headphone output with 6.3 mm jack
- Output power: 35 watt of sine power per channel (4 ohms)
- Elaborate mains adapter
- Shielded toroidal transformer
- Standby power supply for low power consumption in standby mode

MISCELLANEOUS:

- Sturdy full-metal enclosure with solid, brushed aluminium front
- Solid aluminium controls
- Stable feet with damping rubber insert
- Readable, two-line clear text display with adjustable brightness (3 stages)
- System remote control for all functions

FM/DAB TUNER:

- Digital DAB/DAB+ tuner
- FM tuner
- RDS/radio text function
- 40 programmable station presets each for DAB/DAB+ and FM
- Station search (DAB)
- Automatic scanning function (FM)





MC 200

Compact high-end stereo NETWORK/CD/DAB/FM receiver with a max. power output of 150 watts in Hi-Res quality

TUNER:

FREQUENCY RANGE FM
87.5 – 108 MHz

FREQUENCY RANGE DAB/DAB+
174.928 – 239.2 MHz (Band III)

SENSITIVITY FM
-108 dBm

SENSITIVITY DAB/DAB+
-100 dBm

CD PLAYER:

COMPATIBLE DISC FORMATS
CD-Audio, CD-R, CD-RW, MP3, WMA

AMPLIFIER:

OUTPUT POWER

Nominal power:
20 Hz – 20 kHz, THD < 1.0%, 4 Ω 2 x 35 W
20 Hz – 20 kHz, THD < 1.0%, 8 Ω 2 x 25 W
Peak power: 1 kHz, 4 Ω 2 x 75 W

FREQUENCY RESPONSE

CD/Aux/Line 10 Hz – 80 kHz (-3,0 dB)
20 Hz – 20 kHz (+/-0,5 dB)

S/N RATIO

CD/Aux/Line 98 dB (A)
Digital inputs -

INPUT SENSITIVITY

Aux/Line 470 mV/100 kΩ

DIGITAL INPUTS

1x optical (Toslink™)
1x coaxial (cinch)
Supported sampling frequencies: 44.1/48/88.2/96/176.4/192 kHz
Supported bit depths: 16/24 bits

BLUETOOTH® INPUT

Bluetooth® 4.1 / Qualcomm aptX®

NETWORK INPUT

WLAN: 2.4 GHz, 802.11 b/g/n, WPA2, 300Mbps
(up to 192 kHz/24 Bit)
LAN: RJ45
Supported formats: MP3, WMA, AAC, FLAC, APE, WAV
Control over MAGNAT STREAMING APP (available for iOS und Android)
network player, DLNA player, internet radio, multiroom functionality

OPERATING FREQUENCY

2402 - 2480 MHz

MAX. EMITTED POWER ACCORDING TO EN 62479

15.73 dBm

MAX. POWER CONSUMPTION

Maximum: 130 W, Standby: < 0,5 W

AVAILABLE COLOURS

Black

DIMENSIONS (WxHxD)

Main unit: 277 x 132 x 330 mm
Incl. controls and connectors: 277 x 132 x 370 mm
Remote control: 45 x 175 x 20 mm

WEIGHT

5.8 kg

ART.NO. / EAN

D 149 522 R / 40 18843 95228 4

SCOPE OF DELIVERY

MC 200 Receiver
Remote control incl. batteries
FM/DAB areal antenna
Power cord
Instruction manual

